



**MAKINEX®**

Power Solutions

# Power Generator 32 kW

## World's smallest 32kW 480V Dual Phase Generator



**One-Third Size of Tow-Behinds**



**Dual Phase Outlets**
















**15% More Power**

Experience the World's Smallest 32kW Powerhouse. This compact marvel redefines generator capabilities, delivering a remarkable 32kW of 480V single/three-phase power. A mere fraction of the size and weight of comparable towable and SKID generators, it eliminates the need for tow-behind setups. Driven by an advanced radial flux alternator, it excels in high-frequency and inductive load capabilities. With a 13.2G/ 50L fuel tank, enjoy seamless all-day operation. RCD and RCBO protection ensure safety for both equipment and users. Transport with ease as its compact design ensures effortless storage.



### SPECIFICATIONS:

Voltage	120/240V Single Phase; 480V Three Phase
Frequency	60HZ
Max output	28000W/ 30kW
Rated output	25,000W
Rated power factor	0.8
Max Amps single phase	30A @ 240V
Max Amps three phase	50A @ 480V 3Ø
Sockets provided	50 Amp 480V 3-phase / 30 Amp 480V 3-phase / 120V GFCI
Dry weight	772lbs/320KG
Noise level (7m)	72-76dB
Engine type	Twin cylinder Air Cooled Petrol
Engine model	Honda GX690 X 2
Starting system	Electric / Key Start
Displacement	1376CC
Fuel economy	2.6g/9.8 L/h @ 50% LOAD
Fuel tank	13.2g/50L
Dimensions	43.5in/1105mm (L) x 24.8in/632mm (W) x 40.3in/1206mm

Outlets Provided	9kW	16kW 240V	16kW 480V	23kW 480V
50A Three-Phase		 CS8369		 CS8369
50A Single-Phase		 CS6369		
30A Three-Phase	 L15-30R		 L16-30R	 L16-30R
30A Single-Phase	 L6-30R	 L14-30R		 L6-30R
20A Single-Phase	 20A GFCI	 20A GFCI	 20A GFCI	 20A GFCI

**Ideal For:**



Concrete Cutting



Masonry



Back-Up Power



High frequency Applications



Remote Construction




Outdoor events



## Features:



1. Electric/Key Start



2. 2x 30A Single Phase sockets



3. 1 x 50A Three phase socket



4. 13.2g/50L Fuel Tank



5. Easy Maneuverability

## Makinex Generator Range:



1. Power Generator 9 kW



2. Power Generator 16 kW



3. Power Generator 23 kW